

- _____ 12. Turn the radio on by pressing the **PWR** button ①
- _____ 13. Set the Squelch by pressing the **SQL** key ②. The **SQL** ③ icon appears on the display and the squelch level will be shown. Set the Squelch level to 2. After 5 seconds, the display returns to normal.
- _____ 14. Set the Volume level to so that the indicator is in the 10 o'clock position.
- _____ 15. Select Memory Mode by pressing the **V/M** key ④. Verify that the **M** icon appears on the display.
- _____ 16. Rotate the **MAIN** Dial ⑤ to change the memory channel. The list of frequencies and their programmed channel assignments are listed on the next page.
- _____ 17. Verify the Radio-to-TNC cable is connected.

Connecting to the County BBS

- _____ 18. Connect to the County Packet system by entering this command:
cmd: c KE6AGJ-1 [enter]

Verify you see the welcome message.

Creating and Sending Messages

NOTE: See the SOP for procedures for creating Packet Messages.

- _____ 19. Run the **Notepad** Program (Start->Programs->Accessories->Notepad).
- _____ 20. When done writing the message, using the cursor, highlight the entire message to be sent. From the pull-down menu, press **Edit**, then **Copy**.
- _____ 21. Select the HyperTerminal Program. Press **Edit**, then **Paste to Host**. Verify your message was transferred.

3. After the Event

- _____ 22. Disconnect from the County Packet system with this BBS command:
b [enter]

Verify you are logged off and you see the cmd: prompt.

- _____ 23. Turn of the Radio and TNC.
- _____ 24. Close all open Windows programs.
- _____ 25. Shut down the Computer.
- _____ 26. Prepare a list of lessons learned, needed changes to checklists, and requests for additional supplies/equipment.